

HIGH EFFICIENCY 25KW FM TRANSMITTER EM 25000 HE DIG PLUS

The 25KW FM transmitter **EM 25000 HE DIG PLUS** has been created by the OMB center of development for high efficiency transmitters. It consists on the FMA 25000 HE power amplifier and the EM 250 DIG PLUS transmitter. This high efficiency 25KW amplifier is composed by eight 3.5KW amplifying units (FMA 3500 HE). It is also available in Dual Drive version.



MAIN ADVANTAGES

- Eight amplifying units, each composed by four amplifying modules of 1200W with MOSFET technology.
- Each amplifying unit contains three independent switching power supplies connected in parallel to maintain the equipment working in case any of them fails.
- TFT screen and touch keyboard to control and to visualize operation parameters.
- Memory recording of events.
- Speed control of cooling fans according to temperature of power modules so as to optimize consumption and to decrease acoustic contamination.
- Advanced protection against load mismatches without transmission cuts and fast protection in case of excessive reflected power and/or excessive input power.
- Analog telemetry, digital remote control and telemetry RS232, remote control by opened/closed contacts
- Automatic power reduction at night when used in combination with the EM 250 DIG PLUS transmitter.
- Automatic power reduction in case of high temperature, the equipment returns automatically to its rated power value when the temperature reaches back an average value.
- Automatic power reduction in case of excessive reflected power.

broadcast your _ world

GENERAL CHARACTERISTICS

AMPLIFIER FMA 25000 HE	
FREQUENCY RANGE	87.5-108MHz
INPUT RETURN LOSS	-20dB
INPUT POWER	250W
OUTPUT POWER	25KW nominal, manual and automatic adjustable
COOLING	Forced air, speed control of fans
HARMONICS LEVEL	-80dBc
INPUT/OUTPUT IMPEDANCE	50Ω
RF INPUT CONNECTOR	N(F)
RF OUTPUT CONNECTOR	EIA 3+1/8"
RF MONITOR CONNECTOR	BNC(F)
POWER SUPPLY	Three phase: 230VAC (without N) – 380VAC (with N) ±15%, 50/60Hz
CONSUMPTION	38KW
PROTECTIONS	Reflected power, forward power, overdrive, and overcurrent in power modules. Smart temperature protection. Ultra-fast protection against reflected and input power. Real time registration of events. Exciter's inhibition
TELEMETRY AND REMOTE CONTROL	Analog telemetry (direct and reflected power measurements). Digital telemetry and remote control RS232. Remote control by opened/closed contacts
OPERATION TEMPERATURE	0 to +40°C

EXCITER EM 250 DIG PLUS	
FREQUENCY RANGE	87.5-108MHz
FM MODULATION	75KHz (adjustable) peak deviation. Mono 180kF3E and Stereo 256kF3E
AUDIO/MPX INPUT LEVEL	-3.5 @ +12.5dBm @ 75KHz deviation
AUDIO INPUT CONNECTORS	XLR(F)
AUXILIARY CHANNEL (RDS/SCA) INPUT LEVEL	7.5KHz deviation: -12.5 to 3.5dBm and 2KHz deviation: -24 to -8dBm
AUX. CHANNEL INPUT IMPEDANCE	10kOhm
MODULATION DISTORTION	7.5KHz deviation: <0.05%, 0.02% typical; 2KHz deviation: <0.2%, 0.05% typical
S/N MONO RATIO	30 to 20000Hz: >76dB, 86dB typical, CCIR: >75dB, 81dB typical
S/N STEREO RATIO	30 to 20000Hz: >72dB, 77dB typical, CCIR: >68dB, 72dB typical
AUDIO CHANNELS BANDWIDTH	30 to 15000Hz ±0.1dB

broadcast your world

PRE-EMPHASIS TIME CONSTANT	Selectable, 25/50/75 microseconds
RF NOMINAL OUTPUT POWER	250W
TUNING STEPS OF TRANSMITTER	10/100KHz
ALC OUTPUT POWER STABILITY	±3%
SPURIOUS AND HARMONIC EMISSIONS	<80dBc
RF OUTPUT IMPEDANCE	50Ω
RF INPUT POWER CONNECTOR	N
RF SAMPLING CONNECTOR	BNC
POWER SUPPLY	110-230Vac ±15% 50-60Hz
CONSUMPTION	460VA (250W)
OPERATION TEMPERATURE RANGE	0 to 40°C recommended, -10 to 55°C max.
RELATIVE HUMIDITY	Up to 95% without condensation

** The images and/or technical specifications are subject to change without previous notice.*

broadcast your _ world

OMB BROADCAST
www.omb.com

OMB EUROPA
C/ Paraguay 6, P.I. Centrovía
50198 La Muela
Zaragoza, España
europa@omb.com
comercial@omb.com

OMB AMÉRICA
3100NW 72nd. Ave. Unit 112
MIAMI, Florida 33122
USA
usa@omb.com